

#### **Product Features**

- DC 4000 MHz
- +13.5 dBm P1dB at 900 MHz
- +26.5 dBm OIP3 at 900 MHz
- 15.5 dB Gain at 900 MHz
- Single Voltage Supply
- Green SOT-363 SMT Pkg.
- Internally matched to  $50 \Omega$

# Applications

- Mobile Infrastructure
- CATV / DBS
- W-LAN / ISM
- RFID
- Defense / Homeland Security
- Fixed Wireless

# Specifications <sup>(1)</sup>

Parameter	Units	Min	Тур	Max
Operational Bandwidth	MHz	DC		6000
Test Frequency	MHz		900	
Gain	dB		15.6	
Input Return Loss	dB		18	
Output Return Loss	dB		18	
Output IP3 <sup>(2)</sup>	dBm		+26.4	
Output IP2	dBm		+37	
Output P1dB	dBm		+13.4	
Noise Figure	dB		3.4	
Test Frequency	MHz		1900	
Gain	dB	13.5	14.5	15.5
Output IP3 <sup>(2)</sup>	dBm		+24.8	
Output P1dB	dBm		+12.2	
Device Voltage	V		4.23	
Device Current	mA		35	

Test conditions: . T = 25° C, Supply Voltage = +5 V, R<sub>bias</sub> = 22.1 Ω, 50 Ω System.
 3OIP measured with two tones at an output power of -2 dBm/tone separated by 10 MHz. The suppression on the largest IM3 product is used to calculate the 3OIP using a 2:1 rule.

# **Absolute Maximum Rating**

Parameter	Rating
Operating Case Temperature	-40 to +85 °C
Storage Temperature	-55 to +125 °C
DC Voltage	+4.5 V
RF Input Power (continuous)	+10 dBm
Junction Temperature	+250 °C

Operation of this device above any of these parameters may cause permanent damage.

**Product Information** 




### **Product Description**

The AG302-63 is a general-purpose buffer amplifier that offers high dynamic range in a low-cost surface-mount package. At 900 MHz, the AG302-63 typically provides 15.5 dB gain, +26.5 dBm OIP3, and +13.5 dBm P1dB. The device combines dependable performance with consistent quality to maintain MTTF values exceeding 100 years at mounting temperatures of +85° C and is housed in a leadfree/green/RoHS-compliant SOT-363 industry standard SMT package.

The AG302-63 consists of Darlington pair amplifiers using the high reliability InGaP/GaAs HBT technology process technology and only requires DC-blocking capacitors, a bias resistor, and an inductive RF choke for operation.

The broadband MMIC amplifier can be directly applied to various current and next generation wireless technologies such as GPRS, GSM, CDMA, and W-CDMA. In addition, the AG302-63 will work for other various applications within the DC to 4 GHz frequency range such as CATV and fixed wireless.

### **Functional Diagram**



Function	Pin No.
Input	3
Output/Bias	6
Ground	1, 2, 4, 5

# Typical Performance (1)

Parameter	Units	Typical					
Frequency	MHz	500	900	1900	2140		
S21	dB	15.9	15.6	14.5	14.2		
S11	dB	-18	-18	-18	-18		
S22	dB	-20	-18	-18	-15		
Output P1dB	dBm	+13.2	+13.4	+12.2	+11.7		
Output IP3	dBm	+26.6	+26.4	+24.8	+24.3		
Noise Figure	dB	3.3	3.4	3.6	3.6		

## **Ordering Information**

Part No.	Description
AG302-63*	InGaP HBT Gain Block
10502-05	(lead-tin SOT-363 Pkg)
AG302-63G	InGaP HBT Gain Block
10302-030	(lead-free/green/RoHS-compliant SOT-363 Pkg)
AG302-63PCB	700-2400 MHz Fully Assembled Eval. Board
A 771 1 1 1 1 1 1	

This package is being phased out in favor of the green package type which is backwards compatible for existing designs. Refer to Product Change Notification WJPCN06MAY05TC1 on the WJ website.






# Typical Device RF Performance Supply Bias = +5 V, $R_{bias}$ = 22.1 $\Omega$ , $I_{cc}$ = 35 mA

Frequency	MHz	100	500	900	1900	2140	2400	3500	5800
S21	dB	16.0	15.9	15.6	14.5	14.2	13.9	12.5	9.2
S11	dB	-18	-18	-18	-18	-18	-18	-15	-11
S22	dB	-20	-20	-18	-18	-15	-15	-14	-8
Output P1dB	dBm	+13.5	+13.2	+13.4	+12.2	+11.7	+11.6	+9.5	
Output IP3	dBm	+26.6	+26.6	+26.4	+24.8	+24.3	+23.9		
Noise Figure	dB	3.3	3.3	3.4	3.6	3.6	3.7		


Test conditions: T = 25° C, Supply Voltage = +5 V, Device Voltage = 4.23 V, Rbias = 22.1 Ω, Icc = 35 mA typical, 50 Ω System. 1.

3. 30IP measured with two tones at an output power of -2 dBm/tone separated by 10 MHz. The suppression on the largest IM3 product is used to calculate the 30IP using a 2:1 rule
 3. Data is shown as device performance only. Actual implementation for the desired frequency band will be determined by external components shown in the application circuit.









Specifications and information are subject to change without notice

3

2

2.5

1.5

Frequency (GHz)

Frequency (GHz)

3 3.5

0

4

0.5

1

0.5

1 1.5 2 2.5


0





#### Vcc Icc = 35 mA R1 Bias ≷ Resistor C4 Bypass Capacitor C3 0.018 µF L1 ₹ RF Choke RF IN RF OUT AG302-63 C1 C2 Blocking Capacitor Blocking Capacitor

#### **Application Circuit**



#### Recommended Component Values

Reference	Frequency (MHz)						
Designator	50	500	900	1900	2200	2500	3500
L1	820 nH	220 nH	68 nH	27 nH	22 nH	18 nH	15 nH
C1, C2, C4	.018 µF	1000 pF	100 pF	68 pF	68 pF	56 pF	39 pF

1. The proper values for the components are dependent upon the intended frequency of operation. 2. The following nd performance:

ng v	ig values are contained on the evaluation board to achieve optimal broadband					
	Ref. Desig.	Value / Type	Size			
	L1	39 nH wirewound inductor	0603			
	C1, C2	56 pF chip capacitor	0603			
	C3	0.018 µF chip capacitor	0603			
	C4	Do Not Place				
	R1	22.1 $\Omega$ 1% tolerance	0805			

Recommended Bias Resistor Values

S upply Voltage	R1 value	Size
5 V	22.1 ohms	0603
6 V	51 ohms	0805
7 V	80 ohms	1206
8 V	108 ohms	1210
9 V	137 ohms	1210
10 V	166 ohms	1210
12 V	223 ohms	2010

The proper value for R1 is dependent upon the supply voltage and allows for bias stability over temperature. WJ recommends a minimum supply bias of +5 V. A 1% tolerance resistor is recommended.


#### **Typical Device Data**

		S-Parameters (V	$V_{\text{device}} = +4.23$	$V, I_{CC} = 35 \text{ mA},$	$T = 25^{\circ}C$ , cali	ibrated to device	e leads)	
Freq (MHz)	S11 (dB)	S11 (ang)	S21 (dB)	S21 (ang)	S12 (dB)	S12 (ang)	S22 (dB)	S22 (ang)
50	-19.85	-177.05	15.79	177.89	-19.50	1.85	-22.57	-9.39
250	-19.98	175.72	15.72	170.42	-19.97	1.77	-22.62	-20.70
500	-18.01	168.09	15.61	160.75	-19.89	-1.49	-25.70	-57.42
750	-18.03	161.31	15.46	151.46	-19.75	-0.83	-23.67	-81.31
1000	-18.40	155.28	15.23	142.64	-20.03	-5.40	-21.92	-97.33
1250	-18.41	151.47	15.04	133.43	-19.57	-3.15	-20.29	-113.22
1500	-18.66	151.02	14.72	124.92	-19.70	-3.55	-19.00	-123.83
1750	-19.00	148.77	14.42	116.42	-19.61	-2.45	-17.99	-133.36
2000	-19.53	143.58	14.09	108.45	-19.21	-4.88	-17.12	-142.08
2250	-20.76	113.17	13.77	100.67	-19.05	-5.29	-15.05	-130.60
2500	-20.87	111.03	13.52	95.18	-19.25	-9.57	-15.35	-142.08
2750	-19.68	123.77	13.23	87.31	-18.88	-8.74	-15.64	-156.85
3000	-19.28	129.86	12.90	79.66	-18.52	-7.78	-15.96	-175.61
3250	-17.79	131.49	12.55	72.44	-18.46	-10.45	-15.54	163.89
3500	-15.90	129.32	12.20	64.86	-18.38	-12.94	-14.38	142.50
3750	-14.24	123.22	11.76	57.50	-18.15	-16.94	-12.52	126.50
4000	-12.67	119.37	11.34	49.91	-17.95	-17.17	-10.93	117.72
4250	-11.41	115.92	10.89	43.03	-17.83	-21.16	-9.42	109.93
4500	-10.59	112.56	10.41	36.71	-17.67	-22.91	-8.57	104.82
4750	-10.10	109.83	9.99	30.18	-17.43	-25.99	-7.86	102.35
5000	-9.85	106.48	9.64	24.37	-17.45	-26.81	-7.45	102.33
5250	-10.24	105.44	9.33	19.39	-17.45	-29.65	-7.63	102.18
5500	-10.79	104.94	9.06	14.78	-16.94	-30.74	-7.77	103.04
5750	-11.50	106.52	8.93	9.92	-16.70	-31.15	-8.37	104.38
6000	-12.41	105.88	8.77	4.74	-16.46	-33.40	-9.03	103.86

Device S-parameters are available for download on the website at: http://www.wj.com

Specifications and information are subject to change without notice







Specifications and information are subject to change without notice




#### AG302-63G (Green / Lead-free SOT-363 Package) Mechanical Information

This package is lead-free/Green/RoHS-compliant. It is compatible with both lead-free (maximum 260°C reflow temperature) and leaded (maximum 245°C reflow temperature) soldering processes. The plating material on the leads is annealed matte tin over copper.










TOP VIEW










# **Thermal Specifications**

Parameter	Rating
Operating Case Temperature	-40 to +85°C
Thermal Resistance, Rth <sup>(1)</sup>	325° C/W
Junction Temperature, Tjc <sup>(2)</sup>	133° C
Junction Temperature, Tje	155 C

1. The thermal resistance is referenced from the hottest part of the junction to the ground pin (pin 4).

 This corresponds to the typical biasing condition of +4.23V, 35 mA at an 85°C case temperature. A minimum MTTF of 1 million hours is achieved for junction temperatures below 177 °C.

# MITTF vs. GND Lead Temperature




# **Product Marking**

The component will be marked with an "I" designator followed by a two-digit numeric lot code on the top surface of the package.

Tape and reel specifications for this part are located on the website in the "Application Notes" section.

## **MSL / ESD Rating**



MSL Rating: Level 3 Standard: JEDEC Standard J-STD-020

# **Mounting Config. Notes**

- Ground / thermal vias are critical for the proper performance of this device. Vias should use a .35mm (#80 / .0135") diameter drill and have a final plated thru diameter of .25 mm (.010").
- Add as much copper as possible to inner and outer layers near the part to ensure optimal thermal performance
- the part to ensure optimal thermal performance.
  Mounting screws can be added near the part to fasten the board to a heatsink. Ensure that the ground / thermal via region contacts the heatsink.
- Do not put solder mask on the backside of the PC board in the region where the board contacts the heatsink.
   RE trace width depends upon the PC board material and
- 5. RF trace width depends upon the PC board material and construction.
- Use 1 oz. Copper minimum.
- All dimensions are in millimeters (inches). Angles are in degrees.